

# Clock Instructions

---

## Starting Up

- Flip the switch on the back left to turn it on.
- Screen will display “Resume Game, Yes/No - Press No
- Press Enter

## South / Verizon Rinks

- Game Code should default to “4401”
- Press Enter
- Radio Settings should default to “BCAST 1 CHAN 00”
- Press Enter
- Wait 30 seconds for scoreboards and console to connect

## Setting the Main Clock

- Press Set Main Clock
- Enter time using the number pad including seconds to the tenth place
- Squirts = 12 minute periods, Peewee/Bantam = 15 minute periods
- So for 15 minutes it would be 1-5-0-0-0
- Press Enter

## Entering a Penalty

- Press Player Penalty on the Home or Away keypad
- Press Enter
- Enter player number
- Press Enter
- Enter the penalty time without tenths of seconds (defaults to 2:00)
- Press Enter

## Penalties

- Minor – 2:00 for Peewee/Bantam and 1:30 for Squirts
- Double Minor – 4:00 for Peewee/Bantam and 3:00 for Squirts
- Major – 5:00 (don’t clear on goal)
- Misconduct – 10:00 (don’t put on the board)
- Coincidental Minors – 2:00 (don’t put on the board)

## Removing a Penalty

- Press Player Penalty on the Home or Away keypad
- **Don't** press enter
- Use Up/Down arrows to scroll to player to remove
- Press Delete Penalty (or Clear on North rink)
- Press Enter

## Entering a Goal

- Press Goal + 1 on the Home or Away keypad
- Can press Goal -1 if you accidentally gave it to the wrong team

## Period Breaks

- Press Disable Penalty Clocks
- Press Enter
- Set the Main Clock to 1:00 and start the time running
- Horn will sound when time expires
- Press Enable Penalty Clocks
- Press Enter
- Set the Main Clock to the period length

## Changing the Period

- Press Period + 1
- No Period - 1 or Clear option on the South Rink, need to wrap around if you overshoot

## Misc

- At the start of each period the referee will motion if you are ready – respond back
- Do not put a goal on the board until the referee has told you it is a good goal
- Do not put a penalty on the board until the referee has told you what it is
- When the game is over turn off the clock